

Site Preparation Specification

Purpose of Procedure

To assure that the installation of HP instruments and systems can be completed successfully by careful preparation and evaluation of the installation site and by ensuring the availability of appropriate utilities, consumables and supplies.

Customer Responsibilities

Customers should ensure that all necessary operating supplies, consumables and usage dependent items such as columns, vials, syringes and solvents required for the successful installation of instruments and systems are available. Installation sites should be prepared in accordance with the following specifications.

Important Information

If you have problems in providing any of the following, please contact your local HP office for assistance. Assistance with user specific applications may be provided but should be contracted separately. Users of the instrument should be present throughout the installation and familiarization otherwise important operational, maintenance and safety information may be missed.

Procedure Checklist

Dimensions and Weight



Weight: 15 kg
33 lbs.
Depth: 42.4 cm
16.7 in

Height: 18.5 cm
7.3 in
Width: 60.5 cm
23.8 in

Tick Boxes




Power Consumption



Europe:	USA:
220-240V AC	100-120V AC
(±10%)	(±10%)
50 Hz (±5%)	60 Hz (±5%)
100 watts max	
requires one mains socket	



Environmental Conditions:



Temperature:		
Operating:	0° - 40° C	32° - 104° F
Non-operating:	-40° -65° C	-4° -149° F
Maximum rate of change:	5° C/hr	9° F/hr
Rel. Humidity	5 -85% (25° -40° C), non-condensing	
Maximum Altitude:		
Operating:	4,600m	14,950 ft
Non-operating:	15,300m	49,700 ft

